# HPE Aruba Networking CX 6000 Switch Series



### What's new

- It simplifies IT operations with modern Layer 2 switch series that provides entry level, reliable, and convenient wired access connectivity
- The CX 6000 series has convenient built-in 1GbE uplinks and up to 740W of Class 4 PoE for support of access points, client, and IoT devices
- It has compact and fanless 8-port and 12-port models for space-constrained deployments
- The CX 6000 provides flexibility to manage and simplify configurations with HPE Aruba Networking Central, HPE Aruba Networking Switch Multi-Edit Software, easy to use Web GUI, or industry standard CLI

## Overview

The HPE Aruba Networking CX 6000 Switch Series is a modern family of entry level access switches ideal for branch offices, midsize businesses, and small enterprises. Designed for reliable, simple, and secure access, this switch family provides a convenient and cost-effective wired access solution for networks supporting Internet of Things (IoT), mobile, and cloud applications.

Prepare your network for future demands with a powerful ASIC and HPE Aruba Networking CX Switch Operating System for a consistent, and efficient operator experience. This fully-managed series has convenient built-in uplinks with up to 740W of Class 4 PoE to support IoT devices such as security cameras and wireless APs. A compact and fanless model is ideal for use in quiet, small workspaces. The CX 6000 series is easy to deploy and use with flexible management choices, allowing the ideal fit for your business and network environment.

– Ready for software defined networking with REST APIs.

# Features

### Entry-level Layer 2 access switches

The HPE Aruba Networking CX 6000 Switch Series offers Ethernet gigabit connectivity and optional PoE to provide entry-level, reliable, and convenient wired access connectivity for enterprise branch offices and SMB networks.

The switch series delivers a simple, consistent operator experience with the HPE Aruba Networking CX Switch Operating System used across HPE Aruba Networking CX switching platforms.

It has fully-managed enterprise-class switches switches deliver Layer 2 capabilities with support static routing, access control lists (ACLs), robust quality of service (QoS), traffic prioritization, sFlow®, and IPv6.

The CX 6000 series provides right-size deployment with choice of 8, 12, 24, and 48-port 1U models with convenient built-in 1GbE uplinks and up to 740W of Class 4 PoE.

It simplifies ownership with no switch software licensing or subscriptions required.

### AI-ready erformance and power

The HPE Aruba Networking CX 6000 Switch Series is designed with a dedicated ASIC that delivers very low latency, increased packet buffering, and optimized power consumption ideal for AI, Wi-Fi 7, and IoT requirements.

It supports up to 740W IEEE 802.3at Class 4 PoE with up to 30W per port to enable full deployments of wireless access points and IoT devices.

It has up to four built-in wire speed 1GbE uplinks remove bottlenecks at the access layer where users and devices connect.

### Simplified configuration and management

The HPE Aruba Networking CX 6000 Switch Series provides flexibility to manage and simplify configurations with HPE Aruba Networking Central, HPE Aruba Networking Switch Multi-Edit Software, easy-to-use web GUI, or industry-standard CLI.

HPE Aruba Networking Switch Multi-Edit Software introduces automation that allows for rapid network-wide changes and verifies policy conformance post network updates.

The switch series offers unified management across wired, wireless, and WAN using HPE Aruba Networking Central.

It reduces manual IT operation tasks around initial deployment or on-going configuration changes to accommodate adds, moves, and changes with colorless ports using local user roles and local MAC authentication (LMA).

The CX 6000 series is ready for software-defined networking with REST APIs for fine-grained programmability of network tasks.

| Technical specifications | HPE Aruba Networking CX 6000 Switch Series |
|---|---|
| **Power consumption** | Maximum Power (w/o PoE): 49.7W<br>Maximum Power (w/ PoE): 890W<br>Depending on model |
| **Input voltage** | 100–127 VAC / 200–240 VAC |
| **Ports** | 8, 12, 24, or 48 10/100/1000BASE-T ports, depending on model |
| **Latency** | 1 Gbps: 2.3 µSec maximum, depending on model |
| **Switching capacity** | 104 Gbps maximum, depending on model |
| **Throughput** | Up to 77.3 Mpps, depending on model |
| **Memory and processor** | CPU: Dual-core Arm® Cortex-A9 @ 1016 MHz<br>Memory: 4 GB DDR3<br>Flash: 16 GB eMMC |
| **PoE capability** | Up to 740W of Class 4 PoE maximum, depending on model |
| **Operating temperature** | Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) |
| **Management features** | Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software |
| **Warranty** | Limited lifetime warranty. See the warranty duration. |

## SKU comparison

| | HPE Aruba Networking CX 6000 12p 10M/100M/1G Class4 PoE 2p SFP 1G 139W Switch (R8N89B) | HPE Aruba Networking CX 6000 12p 10M/100M/1G Class4 PoE 2p SFP 1G 139W TAA Switch (S4R21A) | HPE Aruba Networking CX 6000 24p 10M/100M/1G 4p SFP 1G Switch (R8N88B) | HPE Aruba Networking CX 6000 24p 10M/100M/1G 4p SFP 1G TAA Switch (S4R27A) | HPE Aruba Networking CX 6000 24p 10M/100M/1G Class4 PoE 4p SFP 1G 370W Switch (R8N87B) |
|---|---|---|---|---|---|
| **Differentiator** | Class 4 PoE/PoE+ | Class 4 PoE/PoE+<br>TAA certified | Non-PoE | Non-PoE<br>TAA certified | Class 4 PoE/PoE+ |
| **Power consumption** | Max. Power (w/o PoE): 19.7W<br>Max. Power (w/ PoE): 165W | Max. Power (w/o PoE): 19.7W<br>Max. Power (w/ PoE): 165W | Max. Power (w/o PoE): 22.4W | Max. Power (w/o PoE): 22.4W | Max. Power (w/o PoE): 26.5W<br>Max. Power (w/ PoE): 409W |
| **Input voltage** | 100–127 VAC / 200–240 VAC | | | | |
| **Ports** | 12 x 10/100/1000BASE-T Class 4 PoE ports<br>2 x 1 G SFP ports<br>2 x 1 GbE ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 12 x 10/100/1000BASE-T Class 4 PoE ports<br>2 x 1 G SFP ports<br>2 x 1 GbE ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 24 x 10/100/1000BASE-T ports<br>4 x 1 G SFP ports<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 24 x 10/100/1000BASE-T ports<br>4 x 1 G SFP ports<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 24 x 10/100/1000BASE-T Class 4 PoE ports<br>4 x 1 G SFP ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port |
| **Latency** | 1 Gbps: 2.3 Sec | 1 Gbps: 2.3 Sec | 1 Gbps: 1.5 Sec | 1 Gbps: 1.5 Sec | 1 Gbps: 1.5 Sec |
| **Switching capacity** | 32 Gbps | 32 Gbps | 56 Gbps | 56 Gbps | 56 Gbps |
| **Throughput** | 23.8 Mpps | 23.8 Mpps | 41.6 Mpps | 41.6 Mpps | 41.6 Mpps |
| **Memory and processor** | CPU: Dual-core Arm® Cortex-A9 @ 1016 MHz<br>Memory: 4 GB DDR3<br>Flash: 16 GB eMMC | | | | |
| **PoE capability** | 139W Class 4 PoE/PoE+ | 139W Class 4 PoE/PoE+ | Non-PoE model | Non-PoE model | 370W Class 4 PoE/PoE+ |

| | HPE Aruba Networking CX 6000 12p 10M/100M/1G Class4 PoE 2p SFP 1G 139W Switch (R8N89B) | HPE Aruba Networking CX 6000 12p 10M/100M/1G Class4 PoE 2p SFP 1G 139W TAA Switch (S4R21A) | HPE Aruba Networking CX 6000 24p 10M/100M/1G 4p SFP 1G Switch (R8N88B) | HPE Aruba Networking CX 6000 24p 10M/100M/1G 4p SFP 1G TAA Switch (S4R27A) | HPE Aruba Networking CX 6000 24p 10M/100M/1G Class4 PoE 4p SFP 1G 370W Switch (R8N87B) |
|---|---|---|---|---|---|
| **Operating temperature** | 32°F to 104°F (0°C to 40°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | 32°F to 104°F (0°C to 40°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) |
| **Management features** | Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software | | | | |
| **Warranty** | Limited lifetime warranty. See the warranty duration. | | | | |

| | HPE Aruba Networking CX 6000 24p 10M/100M/1G Class4 PoE 4p SFP 1G 370W TAA Switch (S4R26A) | HPE Aruba Networking CX 6000 48p 10M/100M/1G 4p SFP 1G Switch (R8N86B) | HPE Aruba Networking CX 6000 48p 10M/100M/1G 4p SFP 1G TAA Switch (S4R25A) | HPE Aruba Networking CX 6000 48p 10M/100M/1G Class4 PoE 4p SFP 1G 370W Switch (R8N85B) | HPE Aruba Networking CX 6000 48p 10M/100M/1G Class4 PoE 4p SFP 1G 370W TAA Switch (S4R24A) |
|---|---|---|---|---|---|
| **Differentiator** | Class 4 PoE/PoE+<br>TAA certified | Non-PoE | Non-PoE<br>TAA certified | Class 4 PoE/PoE+ | Class 4 PoE/PoE+<br>TAA certified |
| **Power consumption** | Max. Power (w/o PoE): 26.5W<br>Max. Power (w/ PoE): 409W | Max. Power (w/o PoE): 35.2W | Max. Power (w/o PoE): 35.2W | Max. Power (w/o PoE): 41.0W<br>Max. Power (w/ PoE): 439W | Max. Power (w/o PoE): 41.0W<br>Max. Power (w/ PoE): 439W |
| **Input voltage** | 100–127 VAC / 200–240 VAC | | | | |
| **Ports** | 24 x 10/100/1000BASE-T Class 4 PoE ports<br>4 x 1 G SFP ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 48 x 10/100/1000BASE-T ports<br>4 x 1 G SFP ports<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 48 x 10/100/1000BASE-T ports<br>4 x 1 G SFP ports<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 48 x 10/100/1000BASE-T Class 4 PoE ports<br>4 x 1 G SFP ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 48 x 10/100/1000BASE-T Class 4 PoE ports<br>4 x 1 G SFP ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port |
| **Latency** | 1 Gbps: 1.5 Sec | 1 Gbps: 1.9 Sec | 1 Gbps: 1.9 Sec | 1 Gbps: 1.9 Sec | 1 Gbps: 1.9 Sec |
| **Switching capacity** | 56 Gbps | 104 Gbps | 104 Gbps | 104 Gbps | 104 Gbps |
| **Throughput** | 41.6 Mpps | 77.3 Mpps | 77.3 Mpps | 77.3 Mpps | 77.3 Mpps |
| **Memory and processor** | CPU: Dual-core Arm® Cortex-A9 @ 1016 MHz<br>Memory: 4 GB DDR3<br>Flash: 16 GB eMMC | | | | |
| **PoE capability** | 370W Class 4 PoE/PoE+ | Non-PoE model | Non-PoE model | 370W Class 4 PoE/PoE+ | 370W Class 4 PoE/PoE+ |
| **Operating temperature** | Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | | | | |
| **Management features** | Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software | | | | |
| **Warranty** | Limited lifetime warranty. See the warranty duration. | | | | |

| | HPE Aruba Networking CX 6000 48p 10M/100M/1G Class4 PoE 4p SFP 1G 740W Switch (R9Y03B) | HPE Aruba Networking CX 6000 48p 10M/100M/1G Class4 PoE 4p SFP 1G 740W TAA Switch (S4R20A) | HPE Aruba Networking CX 6000 8p 10M/100M/1G 2p SFP 1G Switch (S4R22A) | HPE Aruba Networking CX 6000 8p 10M/100M/1G 2p SFP 1G TAA Switch (S4R28A) | HPE Aruba Networking CX 6000 8p 10M/100M/1G Class4 PoE 2p SFP 1G 67W Switch (S4R23A) |
|---|---|---|---|---|---|
| **Differentiator** | Class 4 PoE/PoE+ | Class 4 PoE/PoE+<br>TAA certified | Non-PoE | Non-PoE<br>TAA certified | Class 4 PoE/PoE+ |
| **Power consumption** | Max. Power (w/o PoE): 45.6W<br>Max. Power (w/ PoE): 818W | Max. Power (w/o PoE): 45.6W<br>Max. Power (w/ PoE): 818W | Max. Power (w/o PoE): 13.8W | Max. Power (w/o PoE): 13.8W | Max. Power (w/o PoE): 16.3W<br>Max. Power (w/ PoE): 98W |
| **Input voltage** | 100–127 VAC / 200–240 VAC | | | | |
| **Ports** | 48 x 10/100/1000BASE-T Class 4 PoE ports<br>4 x 1 G SFP ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 48 x 10/100/1000BASE-T Class 4 PoE ports<br>4 x 1 G SFP ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 8 x 10/100/1000BASE-T ports<br>2 x 1 G SFP ports<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 8 x 10/100/1000BASE-T ports<br>2 x 1 G SFP ports<br><br>1 x USB-C console port<br>1 x USB Type-A host port | 8 x 10/100/1000BASE-T Class 4 PoE ports<br>2 x 1 G SFP ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port |
| **Latency** | 1 Gbps: 1.9 Sec | 1 Gbps: 1.9 Sec | 1 Gbps: 3.2 Sec | 1 Gbps: 3.2 Sec | 1 Gbps: 3.2 Sec |
| **Switching capacity** | 104 Gbps | 104 Gbps | 20 Gbps | 20 Gbps | 20 Gbps |
| **Throughput** | 77.3 Mpps | 77.3 Mpps | 14.8 Mpps | 14.8 Mpps | 14.8 Mpps |
| **Memory and processor** | CPU: Dual-core Arm® Cortex-A9 @ 1016 MHz<br>Memory: 4 GB DDR3<br>Flash: 16 GB eMMC | | | | |
| **PoE capability** | 740W of Class 4 PoE/PoE+ | 740W of Class 4 PoE/PoE+ | Non-PoE model | Non-PoE model | 67W Class 4 PoE/PoE+ |
| **Operating temperature** | Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | 32°F to 104°F (0°C to 40°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | 32°F to 104°F (0°C to 40°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) | 32°F to 104°F (0°C to 40°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) |

| | HPE Aruba Networking CX 6000 48p 10M/100M/1G Class4 PoE 4p SFP 1G 740W Switch (R9Y03B) | HPE Aruba Networking CX 6000 48p 10M/100M/1G Class4 PoE 4p SFP 1G 740W TAA Switch (S4R20A) | HPE Aruba Networking CX 6000 8p 10M/100M/1G 2p SFP 1G Switch (S4R22A) | HPE Aruba Networking CX 6000 8p 10M/100M/1G 2p SFP 1G TAA Switch (S4R28A) | HPE Aruba Networking CX 6000 8p 10M/100M/1G Class4 PoE 2p SFP 1G 67W Switch (S4R23A) |
|---|---|---|---|---|---|
| **Management features** | Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software | | | | |
| **Warranty** | Limited lifetime warranty. See the warranty duration. | | | | |

| | HPE Aruba Networking CX 6000 8p 10M/100M/1G Class4 PoE 2p SFP 1G 67W TAA Switch (S4R29A) |
|---|---|
| **Differentiator** | Class 4 PoE/PoE+<br>TAA certified |
| **Power consumption** | Max. Power (w/o PoE): 16.3W<br>Max. Power (w/ PoE): 98W |
| **Input voltage** | 100–127 VAC / 200–240 VAC |
| **Ports** | 8 x 10/100/1000BASE-T Class 4 PoE ports<br>2 x 1 G SFP ports<br>Supports PoE Standards IEEE 802.3af, 802.3at<br><br>1 x USB-C console port<br>1 x USB Type-A host port |
| **Latency** | 1 Gbps: 3.2 Sec |
| **Switching capacity** | 20 Gbps |
| **Throughput** | 14.8 Mpps |
| **Memory and processor** | CPU: Dual-core Arm® Cortex-A9 @ 1016 MHz<br>Memory: 4 GB DDR3<br>Flash: 16 GB eMMC |
| **PoE capability** | 67W Class 4 PoE/PoE+ |
| **Operating temperature** | 32°F to 104°F (0°C to 40°C) up to 5000 ft (1.5 km) derate -1°C for every 1000 ft (305 m) from 5000 ft (1.5 km) to 10000 ft (3.0 km) |
| **Management features** | Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software |
| **Warranty** | Limited lifetime warranty. See the warranty duration. |

# Related Options

The following options are available for these series:

| SKU | Description |
|---|---|
| **Cables/Cable Kits** | |
| R9J32A | HPE Aruba Networking USB-A reversible to USB-C PC-to-Switch 3m Cable |
| R9J33A | HPE Aruba Networking USB-C to USB-C PC-to-Switch 3m Cable |
| JL742A | HPE Aruba Networking X511 12-port Cable Guard |
| **HPE Aruba Networking Software** | |
| JL639AAE | HPE Aruba Networking NetEdit Single Node 1yr Subscription E-STU |
| JL640AAE | HPE Aruba Networking NetEdit Single Node 3yr Subscription E-STU |
| **Mounting Rack/Rail Options** | |
| J9583B | HPE Aruba Networking X414 1U Universal 4-post Rack Mount Kit |
| **Switches** | |
| JL258A | HPE Aruba Networking 2930F 8G PoE+ 2SFP+ Switch |
| JL693A | HPE Aruba Networking 2930F 12G PoE+ 2G/2SFP+ Switch |
| R9Y04A | HPE Aruba Networking CX 6100 48G Class4 PoE 4SFP+ 740W Switch |
| **Transceiver Options** | |
| J4859D | HPE Aruba Networking 1G SFP LC LX 10km SMF Transceiver |
| J4858D | HPE Aruba Networking 1G SFP LC SX 500m OM2 MMF Transceiver |
| J8177E | HPE Aruba Networking 1G SFP RJ45 100m Cat5e Transceiver |

# Related Services

The following services are available for these series:

| SKU | Description |
|---|---|
| **Technology Services** | |
| H82M0E | HPE Aruba Networking 1Y 24x7 Technical Support 6000 48G 740W SVC |
| H82T3E | HPE Aruba Networking 1Y 24x7 Technical Support Volume Tier 26000 48G 740W SVC |
| H82N3E | HPE Aruba Networking 3Y 24x7 Technical Support 6000 48G 740W SVC |
| H82U8E | HPE Aruba Networking 3Y 24x7 Technical Support Volume Tier 26000 48G 740W SVC |
| H82Q9E | HPE Aruba Networking 5Y 24x7 Technical Support 6000 48G 740W SVC |

| | |
|---|---|
| H82X8E | HPE Aruba Networking 5Y 24x7 Technical Support Volume Tier 26000 48G 740W SVC |
| H55D5E | HPE Aruba Networking Foundational Care 1Y 4HR Exch 6000 12G CL4 2SFP SVC |
| H54Q4E | HPE Aruba Networking Foundational Care 1Y 4HR Exch 6000 24G 4SFP SVC |
| H54B3E | HPE Aruba Networking Foundational Care 1Y 4HR Exch 6000 24G CL4 4SFP SVC |
| H53N2E | HPE Aruba Networking Foundational Care 1Y 4HR Exch 6000 48G 4SFP SVC |
| H82L4E | HPE Aruba Networking Foundational Care 1Y 4HR Exch 6000 48G 740W SVC |
| H52Z1E | HPE Aruba Networking Foundational Care 1Y 4HR Exch 6000 48G CL4 4SFP SVC |
| H55K9E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6000 12G CL4 2SFP SVC |
| H54W8E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6000 24G 4SFP SVC |
| H54H7E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6000 24G CL4 4SFP SVC |
| H53U6E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6000 48G 4SFP SVC |
| H82S8E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6000 48G 740W SVC |
| H53F5E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6000 48G CL4 4SFP SVC |
| H55L0E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6000 12G CL4 2SFP SVC |
| H54W9E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6000 24G 4SFP SVC |
| H54H8E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6000 24G CL4 4SFP SVC |
| H53U7E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6000 48G 4SFP SVC |
| H82S9E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6000 48G 740W SVC |
| H53F6E | HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6000 48G CL4 4SFP SVC |
| H55D9E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6000 12G CL4 2SFP SVC |
| H54Q8E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6000 24G 4SFP SVC |
| H54B7E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6000 24G CL4 4SFP SVC |
| H53N6E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6000 48G 4SFP SVC |
| H82L8E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6000 48G 740W SVC |
| H52Z5E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6000 48G CL4 4SFP SVC |
| H55E0E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6000 12G CL4 2SFP SVC |
| H54Q9E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6000 24G 4SFP SVC |
| H54B8E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6000 24G CL4 4SFP SVC |
| H53N7E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6000 48G 4SFP SVC |
| H52Z6E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6000 48G CL4 4SFP SVC |
| H55D8E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6000 12G CL4 2SFP SVC |
| H54Q7E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6000 24G 4SFP SVC |
| H54B6E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6000 24G CL4 4SFP SVC |
| H53N5E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6000 48G 4SFP SVC |
| H52Z4E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6000 48G CL4 4SFP SVC |
| H82L7E | HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6000 48G 740W SVC |

| | |
|---|---|
| H55E2E | HPE Aruba Networking Foundational Care 1Y 6HR CTR 6000 12G CL4 2SFP SVC |
| H54R1E | HPE Aruba Networking Foundational Care 1Y 6HR CTR 6000 24G 4SFP SVC |
| H54C0E | HPE Aruba Networking Foundational Care 1Y 6HR CTR 6000 24G CL4 4SFP SVC |
| H53N9E | HPE Aruba Networking Foundational Care 1Y 6HR CTR 6000 48G 4SFP SVC |
| H52Z8E | HPE Aruba Networking Foundational Care 1Y 6HR CTR 6000 48G CL4 4SFP SVC |
| H55E3E | HPE Aruba Networking Foundational Care 1Y 6HR CTR CDMR 6000 12G CL4 2SFP SVC |
| H54R2E | HPE Aruba Networking Foundational Care 1Y 6HR CTR CDMR 6000 24G 4SFP SVC |
| H54C1E | HPE Aruba Networking Foundational Care 1Y 6HR CTR CDMR 6000 24G CL4 4SFP SVC |
| H53P0E | HPE Aruba Networking Foundational Care 1Y 6HR CTR CDMR 6000 48G 4SFP SVC |
| H52Z9E | HPE Aruba Networking Foundational Care 1Y 6HR CTR CDMR 6000 48G CL4 4SFP SVC |
| H82L9E | HPE Aruba Networking Foundational Care 1Y 24x7 CDMR 6000 48G 740W SVC |
| H82M1E | HPE Aruba Networking Foundational Care 1Y CTR 6000 48G 740W SVC |
| H82M2E | HPE Aruba Networking Foundational Care 1Y CTR CDMR 6000 48G 740W SVC |
| H82L5E | HPE Aruba Networking Foundational Care 1Y NBD 6000 48G 740W SVC |
| H82L6E | HPE Aruba Networking Foundational Care 1Y NBD CDMR 6000 48G 740W SVC |
| H55D3E | HPE Aruba Networking Foundational Care 1Y NBD Exch 6000 12G CL4 2SFP SVC |
| H54Q2E | HPE Aruba Networking Foundational Care 1Y NBD Exch 6000 24G 4SFP SVC |
| H54B1E | HPE Aruba Networking Foundational Care 1Y NBD Exch 6000 24G CL4 4SFP SVC |
| H53N0E | HPE Aruba Networking Foundational Care 1Y NBD Exch 6000 48G 4SFP SVC |
| H82L2E | HPE Aruba Networking Foundational Care 1Y NBD Exch 6000 48G 740W SVC |
| H52Y9E | HPE Aruba Networking Foundational Care 1Y NBD Exch 6000 48G CL4 4SFP SVC |
| H55D4E | HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6000 12G CL4 2SFP SVC |
| H54Q3E | HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6000 24G 4SFP SVC |
| H54B2E | HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6000 24G CL4 4SFP SVC |
| H53N1E | HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6000 48G 4SFP SVC |
| H52Z0E | HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6000 48G CL4 4SFP SVC |
| H82L3E | HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6000 48G 740W SVC |
| H55K5E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6000 12G CL4 2SFP SVC |
| H54W4E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6000 24G 4SFP SVC |
| H54H3E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6000 24G CL4 4SFP SVC |
| H53U2E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6000 48G 4SFP SVC |
| H82S4E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6000 48G 740W SVC |
| H53F1E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6000 48G CL4 4SFP SVC |
| H55K6E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6000 12G CL4 2SFP SVC |
| H54W5E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6000 24G 4SFP SVC |
| H54H4E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6000 24G CL4 4SFP SVC |

| | |
|---|---|
| H53U3E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6000 48G 4SFP SVC |
| H82S5E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6000 48G 740W SVC |
| H53F2E | HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6000 48G CL4 4SFP SVC |
| H55D6E | HPE Aruba Networking Foundational Care 1Y NBD Onsite 6000 12G CL4 2SFP SVC |
| H54Q5E | HPE Aruba Networking Foundational Care 1Y NBD Onsite 6000 24G 4SFP SVC |
| H54B4E | HPE Aruba Networking Foundational Care 1Y NBD Onsite 6000 24G CL4 4SFP SVC |
| H53N3E | HPE Aruba Networking Foundational Care 1Y NBD Onsite 6000 48G 4SFP SVC |
| H52Z2E | HPE Aruba Networking Foundational Care 1Y NBD Onsite 6000 48G CL4 4SFP SVC |
| H55D7E | HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6000 12G CL4 2SFP SVC |
| H54Q6E | HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6000 24G 4SFP SVC |
| H54B5E | HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6000 24G CL4 4SFP SVC |
| H53N4E | HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6000 48G 4SFP SVC |
| H52Z3E | HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6000 48G CL4 4SFP SVC |
| H55E6E | HPE Aruba Networking Foundational Care 3Y 4HR Exch 6000 12G CL4 2SFP SVC |
| H54R5E | HPE Aruba Networking Foundational Care 3Y 4HR Exch 6000 24G 4SFP SVC |
| H54C4E | HPE Aruba Networking Foundational Care 3Y 4HR Exch 6000 24G CL4 4SFP SVC |
| H53P3E | HPE Aruba Networking Foundational Care 3Y 4HR Exch 6000 48G 4SFP SVC |
| H82M5E | HPE Aruba Networking Foundational Care 3Y 4HR Exch 6000 48G 740W SVC |
| H53A2E | HPE Aruba Networking Foundational Care 3Y 4HR Exch 6000 48G CL4 4SFP SVC |
| H55M3E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6000 12G CL4 2SFP SVC |
| H54Y2E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6000 24G 4SFP SVC |
| H54K1E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6000 24G CL4 4SFP SVC |
| H53W0E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6000 48G 4SFP SVC |
| H82U2E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6000 48G 740W SVC |
| H53G9E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6000 48G CL4 4SFP SVC |
| H55M4E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6000 12G CL4 2SFP SVC |
| H54Y3E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6000 24G 4SFP SVC |
| H54K2E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6000 24G CL4 4SFP SVC |
| H53W1E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6000 48G 4SFP SVC |
| H82U3E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6000 48G 740W SVC |
| H53H0E | HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6000 48G CL4 4SFP SVC |
| H55F2E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6000 12G CL4 2SFP SVC |
| H54S1E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6000 24G 4SFP SVC |
| H54D0E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6000 24G CL4 4SFP SVC |
| H53P9E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6000 48G 4SFP SVC |
| H82N1E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6000 48G 740W SVC |

| | |
|---|---|
| H53A8E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6000 48G CL4 4SFP SVC |
| H55F3E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6000 12G CL4 2SFP SVC |
| H54S2E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6000 24G 4SFP SVC |
| H54D1E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6000 24G CL4 4SFP SVC |
| H53Q0E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6000 48G 4SFP SVC |
| H53A9E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6000 48G CL4 4SFP SVC |
| H55F1E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6000 12G CL4 2SFP SVC |
| H54S0E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6000 24G 4SFP SVC |
| H54C9E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6000 24G CL4 4SFP SVC |
| H53P8E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6000 48G 4SFP SVC |
| H53A7E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6000 48G CL4 4SFP SVC |
| H82N0E | HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6000 48G 740W SVC |
| H55F5E | HPE Aruba Networking Foundational Care 3Y 6HR CTR 6000 12G CL4 2SFP SVC |
| H54S4E | HPE Aruba Networking Foundational Care 3Y 6HR CTR 6000 24G 4SFP SVC |
| H54D3E | HPE Aruba Networking Foundational Care 3Y 6HR CTR 6000 24G CL4 4SFP SVC |
| H53Q2E | HPE Aruba Networking Foundational Care 3Y 6HR CTR 6000 48G 4SFP SVC |
| H53B1E | HPE Aruba Networking Foundational Care 3Y 6HR CTR 6000 48G CL4 4SFP SVC |
| H55F6E | HPE Aruba Networking Foundational Care 3Y 6HR CTR CDMR 6000 12G CL4 2SFP SVC |
| H54S5E | HPE Aruba Networking Foundational Care 3Y 6HR CTR CDMR 6000 24G 4SFP SVC |
| H54D4E | HPE Aruba Networking Foundational Care 3Y 6HR CTR CDMR 6000 24G CL4 4SFP SVC |
| H53Q3E | HPE Aruba Networking Foundational Care 3Y 6HR CTR CDMR 6000 48G 4SFP SVC |
| H53B2E | HPE Aruba Networking Foundational Care 3Y 6HR CTR CDMR 6000 48G CL4 4SFP SVC |
| H82N2E | HPE Aruba Networking Foundational Care 3Y 24x7 CDMR 6000 48G 740W SVC |
| H82N4E | HPE Aruba Networking Foundational Care 3Y CTR 6000 48G 740W SVC |
| H82N5E | HPE Aruba Networking Foundational Care 3Y CTR CDMR 6000 48G 740W SVC |
| H82M6E | HPE Aruba Networking Foundational Care 3Y NBD 6000 48G 740W SVC |
| H82M7E | HPE Aruba Networking Foundational Care 3Y NBD CDMR 6000 48G 740W SVC |
| H55E5E | HPE Aruba Networking Foundational Care 3Y NBD Exch 6000 12G CL4 2SFP SVC |
| H54R4E | HPE Aruba Networking Foundational Care 3Y NBD Exch 6000 24G 4SFP SVC |
| H54C3E | HPE Aruba Networking Foundational Care 3Y NBD Exch 6000 24G CL4 4SFP SVC |
| H53P2E | HPE Aruba Networking Foundational Care 3Y NBD Exch 6000 48G 4SFP SVC |
| H82M4E | HPE Aruba Networking Foundational Care 3Y NBD Exch 6000 48G 740W SVC |
| H53A1E | HPE Aruba Networking Foundational Care 3Y NBD Exch 6000 48G CL4 4SFP SVC |
| H55E4E | HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6000 12G CL4 2SFP SVC |
| H54R3E | HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6000 24G 4SFP SVC |
| H54C2E | HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6000 24G CL4 4SFP SVC |

| | |
|---|---|
| H53P1E | HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6000 48G 4SFP SVC |
| H53A0E | HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6000 48G CL4 4SFP SVC |
| H82M3E | HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6000 48G 740W SVC |
| H55L9E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6000 12G CL4 2SFP SVC |
| H54X8E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6000 24G 4SFP SVC |
| H54J7E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6000 24G CL4 4SFP SVC |
| H53V6E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6000 48G 4SFP SVC |
| H82T8E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6000 48G 740W SVC |
| H53G5E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6000 48G CL4 4SFP SVC |
| H55M0E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6000 12G CL4 2SFP SVC |
| H54X9E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6000 24G 4SFP SVC |
| H54J8E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6000 24G CL4 4SFP SVC |
| H53V7E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6000 48G 4SFP SVC |
| H82T9E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6000 48G 740W SVC |
| H53G6E | HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6000 48G CL4 4SFP SVC |
| H55E7E | HPE Aruba Networking Foundational Care 3Y NBD Onsite 6000 12G CL4 2SFP SVC |
| H54R6E | HPE Aruba Networking Foundational Care 3Y NBD Onsite 6000 24G 4SFP SVC |
| H54C5E | HPE Aruba Networking Foundational Care 3Y NBD Onsite 6000 24G CL4 4SFP SVC |
| H53P4E | HPE Aruba Networking Foundational Care 3Y NBD Onsite 6000 48G 4SFP SVC |
| H53A3E | HPE Aruba Networking Foundational Care 3Y NBD Onsite 6000 48G CL4 4SFP SVC |
| H55E8E | HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6000 12G CL4 2SFP SVC |
| H54R7E | HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6000 24G 4SFP SVC |
| H54C6E | HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6000 24G CL4 4SFP SVC |
| H53P5E | HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6000 48G 4SFP SVC |
| H53A4E | HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6000 48G CL4 4SFP SVC |
| H55H2E | HPE Aruba Networking Foundational Care 5Y 4HR Exch 6000 12G CL4 2SFP SVC |
| H54U1E | HPE Aruba Networking Foundational Care 5Y 4HR Exch 6000 24G 4SFP SVC |
| H54F0E | HPE Aruba Networking Foundational Care 5Y 4HR Exch 6000 24G CL4 4SFP SVC |
| H53R9E | HPE Aruba Networking Foundational Care 5Y 4HR Exch 6000 48G 4SFP SVC |
| H82Q1E | HPE Aruba Networking Foundational Care 5Y 4HR Exch 6000 48G 740W SVC |
| H53C8E | HPE Aruba Networking Foundational Care 5Y 4HR Exch 6000 48G CL4 4SFP SVC |
| H55Q3E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6000 12G CL4 2SFP SVC |
| H55B2E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6000 24G 4SFP SVC |
| H54N1E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6000 24G CL4 4SFP SVC |
| H53Z0E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6000 48G 4SFP SVC |
| H82X2E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6000 48G 740W SVC |

| | |
|---|---|
| H53K9E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6000 48G CL4 4SFP SVC |
| H55Q4E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6000 12G CL4 2SFP SVC |
| H55B3E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6000 24G 4SFP SVC |
| H54N2E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6000 24G CL4 4SFP SVC |
| H53Z1E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6000 48G 4SFP SVC |
| H82X3E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6000 48G 740W SVC |
| H53L0E | HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6000 48G CL4 4SFP SVC |
| H55H8E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6000 12G CL4 2SFP SVC |
| H54U7E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6000 24G 4SFP SVC |
| H54F6E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6000 24G CL4 4SFP SVC |
| H53S5E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6000 48G 4SFP SVC |
| H82Q7E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6000 48G 740W SVC |
| H53D4E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6000 48G CL4 4SFP SVC |
| H55H9E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6000 12G CL4 2SFP SVC |
| H54U8E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6000 24G 4SFP SVC |
| H54F7E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6000 24G CL4 4SFP SVC |
| H53S6E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6000 48G 4SFP SVC |
| H53D5E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6000 48G CL4 4SFP SVC |
| H55H7E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6000 12G CL4 2SFP SVC |
| H54U6E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6000 24G 4SFP SVC |
| H54F5E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6000 24G CL4 4SFP SVC |
| H53S4E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6000 48G 4SFP SVC |
| H53D3E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6000 48G CL4 4SFP SVC |
| H82Q6E | HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6000 48G 740W SVC |
| H55J1E | HPE Aruba Networking Foundational Care 5Y 6HR CTR 6000 12G CL4 2SFP SVC |
| H54V0E | HPE Aruba Networking Foundational Care 5Y 6HR CTR 6000 24G 4SFP SVC |
| H54F9E | HPE Aruba Networking Foundational Care 5Y 6HR CTR 6000 24G CL4 4SFP SVC |
| H53S8E | HPE Aruba Networking Foundational Care 5Y 6HR CTR 6000 48G 4SFP SVC |
| H53D7E | HPE Aruba Networking Foundational Care 5Y 6HR CTR 6000 48G CL4 4SFP SVC |
| H55J2E | HPE Aruba Networking Foundational Care 5Y 6HR CTR CDMR 6000 12G CL4 2SFP SVC |
| H54V1E | HPE Aruba Networking Foundational Care 5Y 6HR CTR CDMR 6000 24G 4SFP SVC |
| H54G0E | HPE Aruba Networking Foundational Care 5Y 6HR CTR CDMR 6000 24G CL4 4SFP SVC |
| H53S9E | HPE Aruba Networking Foundational Care 5Y 6HR CTR CDMR 6000 48G 4SFP SVC |
| H53D8E | HPE Aruba Networking Foundational Care 5Y 6HR CTR CDMR 6000 48G CL4 4SFP SVC |
| H82Q8E | HPE Aruba Networking Foundational Care 5Y 24x7 CDMR 6000 48G 740W SVC |
| H82R0E | HPE Aruba Networking Foundational Care 5Y CTR 6000 48G 740W SVC |

| | |
|---|---|
| H82R1E | HPE Aruba Networking Foundational Care 5Y CTR CDMR 6000 48G 740W SVC |
| H82Q2E | HPE Aruba Networking Foundational Care 5Y NBD 6000 48G 740W SVC |
| H82Q3E | HPE Aruba Networking Foundational Care 5Y NBD CDMR 6000 48G 740W SVC |
| H55H1E | HPE Aruba Networking Foundational Care 5Y NBD Exch 6000 12G CL4 2SFP SVC |
| H54U0E | HPE Aruba Networking Foundational Care 5Y NBD Exch 6000 24G 4SFP SVC |
| H54E9E | HPE Aruba Networking Foundational Care 5Y NBD Exch 6000 24G CL4 4SFP SVC |
| H53R8E | HPE Aruba Networking Foundational Care 5Y NBD Exch 6000 48G 4SFP SVC |
| H82Q0E | HPE Aruba Networking Foundational Care 5Y NBD Exch 6000 48G 740W SVC |
| H53C7E | HPE Aruba Networking Foundational Care 5Y NBD Exch 6000 48G CL4 4SFP SVC |
| H55H0E | HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6000 12G CL4 2SFP SVC |
| H54T9E | HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6000 24G 4SFP SVC |
| H54E8E | HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6000 24G CL4 4SFP SVC |
| H53R7E | HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6000 48G 4SFP SVC |
| H53C6E | HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6000 48G CL4 4SFP SVC |
| H82P9E | HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6000 48G 740W SVC |
| H55P9E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6000 12G CL4 2SFP SVC |
| H55A8E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6000 24G 4SFP SVC |
| H54M7E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6000 24G CL4 4SFP SVC |
| H53Y6E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6000 48G 4SFP SVC |
| H82W8E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6000 48G 740W SVC |
| H53K5E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6000 48G CL4 4SFP SVC |
| H55Q0E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6000 12G CL4 2SFP SVC |
| H55A9E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6000 24G 4SFP SVC |
| H54M8E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6000 24G CL4 4SFP SVC |
| H53Y7E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6000 48G 4SFP SVC |
| H82W9E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6000 48G 740W SVC |
| H53K6E | HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6000 48G CL4 4SFP SVC |
| H55H3E | HPE Aruba Networking Foundational Care 5Y NBD Onsite 6000 12G CL4 2SFP SVC |
| H54U2E | HPE Aruba Networking Foundational Care 5Y NBD Onsite 6000 24G 4SFP SVC |
| H54F1E | HPE Aruba Networking Foundational Care 5Y NBD Onsite 6000 24G CL4 4SFP SVC |
| H53S0E | HPE Aruba Networking Foundational Care 5Y NBD Onsite 6000 48G 4SFP SVC |
| H53C9E | HPE Aruba Networking Foundational Care 5Y NBD Onsite 6000 48G CL4 4SFP SVC |
| H55H4E | HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6000 12G CL4 2SFP SVC |
| H54U3E | HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6000 24G 4SFP SVC |
| H54F2E | HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6000 24G CL4 4SFP SVC |
| H53S1E | HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6000 48G 4SFP SVC |

| | |
|---|---|
| H53D0E | HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6000 48G CL4 4SFP SVC |
| H55E1E | HPE Aruba Networking Software+Technical Support 1Y 6000 12G CL4 2SFP SVC |
| H54R0E | HPE Aruba Networking Software+Technical Support 1Y 6000 24G 4SFP SVC |
| H54B9E | HPE Aruba Networking Software+Technical Support 1Y 6000 24G CL4 4SFP SVC |
| H53N8E | HPE Aruba Networking Software+Technical Support 1Y 6000 48G 4SFP SVC |
| H52Z7E | HPE Aruba Networking Software+Technical Support 1Y 6000 48G CL4 4SFP SVC |
| H55L4E | HPE Aruba Networking Software+Technical Support 1Y Vol T2 6000 12G CL4 2SFP SVC |
| H54X3E | HPE Aruba Networking Software+Technical Support 1Y Vol T2 6000 24G 4SFP SVC |
| H54J2E | HPE Aruba Networking Software+Technical Support 1Y Vol T2 6000 24G CL4 4SFP SVC |
| H53V1E | HPE Aruba Networking Software+Technical Support 1Y Vol T2 6000 48G 4SFP SVC |
| H53G0E | HPE Aruba Networking Software+Technical Support 1Y Vol T2 6000 48G CL4 4SFP SVC |
| H55F4E | HPE Aruba Networking Software+Technical Support 3Y 6000 12G CL4 2SFP SVC |
| H54S3E | HPE Aruba Networking Software+Technical Support 3Y 6000 24G 4SFP SVC |
| H54D2E | HPE Aruba Networking Software+Technical Support 3Y 6000 24G CL4 4SFP SVC |
| H53Q1E | HPE Aruba Networking Software+Technical Support 3Y 6000 48G 4SFP SVC |
| H53B0E | HPE Aruba Networking Software+Technical Support 3Y 6000 48G CL4 4SFP SVC |
| H55M9E | HPE Aruba Networking Software+Technical Support 3Y Vol T2 6000 12G CL4 2SFP SVC |
| H54Y8E | HPE Aruba Networking Software+Technical Support 3Y Vol T2 6000 24G 4SFP SVC |
| H54K7E | HPE Aruba Networking Software+Technical Support 3Y Vol T2 6000 24G CL4 4SFP SVC |
| H53W6E | HPE Aruba Networking Software+Technical Support 3Y Vol T2 6000 48G 4SFP SVC |
| H53H5E | HPE Aruba Networking Software+Technical Support 3Y Vol T2 6000 48G CL4 4SFP SVC |
| H55J0E | HPE Aruba Networking Software+Technical Support 5Y 6000 12G CL4 2SFP SVC |
| H54U9E | HPE Aruba Networking Software+Technical Support 5Y 6000 24G 4SFP SVC |
| H54F8E | HPE Aruba Networking Software+Technical Support 5Y 6000 24G CL4 4SFP SVC |
| H53S7E | HPE Aruba Networking Software+Technical Support 5Y 6000 48G 4SFP SVC |
| H53D6E | HPE Aruba Networking Software+Technical Support 5Y 6000 48G CL4 4SFP SVC |
| H55Q9E | HPE Aruba Networking Software+Technical Support 5Y Vol T2 6000 12G CL4 2SFP SVC |
| H55B8E | HPE Aruba Networking Software+Technical Support 5Y Vol T2 6000 24G 4SFP SVC |
| H54N7E | HPE Aruba Networking Software+Technical Support 5Y Vol T2 6000 24G CL4 4SFP SVC |
| H53Z6E | HPE Aruba Networking Software+Technical Support 5Y Vol T2 6000 48G 4SFP SVC |
| H53L5E | HPE Aruba Networking Software+Technical Support 5Y Vol T2 6000 48G CL4 4SFP SVC |

# HPE Aruba Networking Services

HPE Aruba Networking services simplify and accelerate the network technology lifecycle, enabling your network to scale with better predictability and cost-effectiveness. Whether you operate your own network and need to improve your IT efficiencies, or you want to offload some of the burden, we have the services you need to reach your goals.

Learn more about what HPE Services - Aruba Networking has to offer at: hpe.com/edge/services

### Support Services

Our support portfolio provides the essential support elements as well as proactive and preventive features to help you improve your team's productivity and get the most from your network. Our support customers benefit from faster issue resolution, simplified operations and efficiencies, and reduced network issues.

### Professional Services

With deep intellectual capital and purpose-built tools, our team delivers a range of standard and custom professional services designed to accelerate your value from HPE Aruba Networking technology.

Project based services include:

— Planning, audit, and assessment
— Architecture review and design
— Deployment, migration, and knowledge transfer

Annual subscription services include:

— Network optimization
— Intelligent Operations
— Customer Experience Management

Our Education Services allow your team to come up to speed quickly.

### GreenLake for Networking

Deliver innovative business outcomes by leveraging new ways to consume, deploy and manage networks.

For additional technical information, available models and options, please reference the QuickSpecs

Visit HPE.com

Chat now

© Copyright 2026 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Parts and Materials: HPE will provide HPE-supported replacement parts and materials required to maintain the covered hardware.

Parts and components that have reached their maximum supported lifetime and/or the maximum usage limitations as set forth in the manufacturer's operating manual, product quick-specs, or the technical product data sheet will not be provided, repaired, or replaced as part of these services.

Arm is a registered trademark of Arm Limited. sFlow is a registered trademark of InMon Corp. All third-party marks are property of their respective owners.

Image may differ from the actual product.

PSN1014098570NLEN, October, 2026.

HEWLETT PACKARD ENTERPRISE

hpe.com